

LINDY®

CONNECTION PERFECTION

3 Port HDMI Switch

User Manual

English




LINDY No. 38033

www.lindy.com


Product Information

Front Panel:




Connect your HDMI sources to one of the 3 input ports

Rear Panel:



Connect your HDTV to the output port
This switch has an optional PSU port. If your HDMI ports, on your source device do not support power over HDMI then you will need to use an appropriate power supply. Please contact LINDY if you require this.

Side Panel:



Connect the IR receiver extension cable to this port

Introduction

Thank you for purchasing the LINDY 3 Port HDMI Switch. This switch allows you to connect three HDMI devices to a single HDMI equipped TV or projector and then switch between them using a push button or remote control.

The maximum recommended cable transmission distance is a total of 30m from the source to the display. This can be made up with 15m from the source to the switch and 15m from the switch to the display. Longer distances may be possible but this does depend on the quality of the source, the display and the connecting cables. We recommend you use LINDY Premium Gold cables for the best possible performance.

The HDMI Switch also supports DVI-D signals when used with appropriate DVI-D to HDMI adapters or DVI-D to HDMI cables.

Features

- HDMI 1.3b, HDCP 1.1 and DVI 1.0 compatible
- LED channel selection indicators
- 12-bit deep colour
- Ideal for home theatre integration, presentation, conference rooms and retail stores
- Supports high resolution input:
 - PC: Up to 1920 x 1200
 - HDTV: Up to 1080p
- Easy to install and simple to operate
- Input source auto detects when an active source is connected

Package Contents

- LINDY 3 Port HDMI Switch
- Infra-red remote
- IR receiver extension cable
- This User Manual

Connection and Operation

1. Connect the HDMI cables from your source devices to the **HDMI Input** ports 1, 2 & 3
2. Connect an HDMI cable from your display (monitor or projector) into the **HDMI Output** port on the switch
3. Select the desired input as follows:

Manual Switching

On the top panel, press the **Select** button until the desired input is selected. Each press will cycle to the next input in turn: 1-2-3 then back to 1. The current input can be identified by the LED on the switch.

From the remote control

Plug the IR extender cable into the switch and then select the input you require from the remote control.

Notes on using DVI equipped devices:

To connect DVI equipped devices you can use either modular DVI/HDMI adapters or DVI/HDMI adapter cables. Be aware that DVI is a 'video only' interface; audio signals are not supported when using DVI source devices. Also, please note that DVI equipped displays must support HDCP signal decoding to display HDCP protected HDMI signals. HDCP compatible displays will normally feature the **HD Ready** logo.

Technical Information

- Frequency bandwidth: 2.5Gbps
- Inputs: 3 x HDMI Female ports (Type A connector)
- Output: 1 x HDMI Female port (Type A connector)
- Dimensions: 80 x 57 x 18mm (WxDxH)

CE/FCC Statement

CE

This device complies with the European Regulations for Electromagnetic Compatibility (EMC) of the European Union and it is equipped with the CE mark. This unit has to be used with high quality shielded connection cables. Only if these high quality shielded cables are used it can be sure that the EMC compatibility is not adversely influenced.

FCC

Shielded cables must be used with this equipment to maintain compliance with radio frequency energy emission regulations and ensure a suitably high level of immunity to electromagnetic disturbances.

This equipment has been tested and found to comply with the limits for a Class B Digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna
- Increase the separation between the equipment and receiver
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected
- Consult the dealer or an experienced technician for help

You are cautioned that changes or modifications not expressly approved by the party responsible for compliance could void your authority to operate the equipment.

Recycling Information



WEEE (Waste of Electrical and Electronic Equipment), Recycling of Electronic Products

United Kingdom

In 2006 the European Union introduced regulations (WEEE) for the collection and recycling of all waste electrical and electronic equipment. It is no longer allowable to simply throw away electrical and electronic equipment. Instead, these products must enter the recycling process.

Each individual EU member state has implemented the WEEE regulations into national law in slightly different ways. Please follow your national law when you want to dispose of any electrical or electronic products.

More details can be obtained from your national WEEE recycling agency.

Germany

Die Europäische Union hat mit der WEEE Richtlinie umfassende Regelungen für die Verschrottung und das Recycling von Elektro- und Elektronikprodukten geschaffen. Diese wurden von der Bundesregierung im Elektro- und Elektronikgerätegesetz – ElektroG in deutsches Recht umgesetzt.

Dieses Gesetz verbietet vom 24. März 2006 an das Entsorgen von entsprechenden, auch alten, Elektro- und Elektronikgeräten über die Hausmülltonne! Diese Geräte müssen den lokalen Sammelsystemen bzw. örtlichen Sammelstellen zugeführt werden! Dort werden sie kostenlos entgegen genommen. Die Kosten für den weiteren Recyclingprozess übernimmt die Gesamtheit der Gerätehersteller.

France

En 2006, l'union Européenne a introduit la nouvelle réglementation (DEEE) pour le recyclage de tout équipement électrique et électronique.

Chaque Etat membre de l'Union Européenne a mis en application la nouvelle réglementation DEEE de manières légèrement différentes. Veuillez suivre le décret d'application correspondant à l'élimination des déchets électriques ou électroniques de votre pays.

Italy

Nel 2006 l'unione europea ha introdotto regolamentazioni (WEEE) per la raccolta e il riciclo di apparecchi elettrici ed elettronici. Non è più consentito semplicemente gettare queste apparecchiature, devono essere riciclate.

Ogni stato membro dell' EU ha tramutato le direttive WEEE in leggi statali in varie misure. Fare riferimento alle leggi del proprio Stato quando si dispone di un apparecchio elettrico o elettronico.

Per ulteriori dettagli fare riferimento alla direttiva WEEE sul riciclaggio del proprio Stato.

LINDY No. 38033

www.lindy.com



1st Edition January 2009